

Interface

Quick
StartInterface
SetupAdvanced
SetupAccess
Management

Maintenance

Status

Help

Internet

LAN

Wireless

QoS

VPI : 0 (range: 0~255)

VCI : 32 (range: 1~65535)

نقوم بوضع القيم
التاليةVPI=0
VCI=32

ATM QoS : UBR ▾

PCR : 0 cells/second

SCR : 0 cells/second

MBS : 0 cells



Encapsulation

ISP : Dynamic IP Address Static IP Address PPPoA/PPPoE Bridge Mode

نختار

PPPoA/PPPoE

PPPoE/PPPoA

Servicename :

Username : ayatv

Password :

Encapsulation : PPPoE LLC ▾

Bridge Interface : Activated Deactivated

نقوم بوضع اليوزر نيم والباسورد

IPTV الافتراضيين لخدمة

Username: ayatv

Password: iptvaya

نقوم باختيار القيمة
Activated
للخيار
Bridge Interface

Interface

Quick
StartInterface
SetupAdvanced
SetupAccess
Management

Maintenance

Status

Help

Internet

LAN

Wireless

Connection Setting

Bridge Interface : Activated DeactivatedConnection : Always On (Recommended)
 Connect On-Demand (Close if idle for 0 minutes)
 Connect Manually

TCP MSS Option : TCP MSS(default:1400) 1400 bytes

IP Address

Get IP Address : Static Dynamic

Static IP Address : 0.0.0.0

IP Subnet Mask : 0.0.0.0

Gateway : 0.0.0.0

NAT : Enable ▼

Default Route : Yes No

TCP MTU Option : TCP MTU(default:1480) 1480 bytes

Dynamic Route : RIP2-B ▼ Direction : Both ▼

Multicast : IGMP v2 ▼

نضع القيمة IGMP v2
للخيار Multicastنضع القيمة No للخيار
Default Route

SAVE

DELETE

Advanced

Quick
StartInterface
SetupAdvanced
SetupAccess
Management

Maintenance

Status

Help

Firewall

Routing



NAT

QoS

VLAN

ADSL

Routing Table List

#	Dest IP	Mask	Gateway IP	Metric	Device	Use	Edit	Drop
1	10.10.10.5	32	10.10.10.5	1	poe4	0		
2	10.237.239.1	32	10.237.239.1	1	poe0	0		
3	192.168.1.0	24	192.168.1.1	1	enet0	5359248		
4	10.237.239.0	24	PVC0	1	poe0	15		
5	default	0	Node5	2	poe4	3769840		

ADD ROUTE

Advanced

Quick
StartInterface
SetupAdvanced
SetupAccess
Management

Maintenance

Status

Help

Firewall

Routing

NAT

QoS

VLAN

ADSL

Static Route

Destination IP Address : 10.237.239.0

IP Subnet Mask : 255.255.255.0

Gateway IP Address : 0.0.0.0 PVC0 ▼

Metric : 1

Announced in RIP : Yes ▼



نقوم بوضع القيم كما في الصورة التالية

SAVE

DELETE

BACK

CANCEL